




HP Pavilion p6 Hard Drive Replacement

How to upgrade or replace you Hard Drive in you HP Pavilion p6 compoter.

Written By: Oli



INTRODUCTION


How to upgrade or replace you Hard Drive in you HP Pavilion p6 computer.







TOOLS:


- [Essential Electronics Toolkit](#) (1)
-




Step 1 — Hard Drive



-  Before you start make sure that all of the leads have been disconnected from the computer.
-  It is strongly recommended to wait at least 15 minutes after turning it off to allow the computer and internal components to cool down.
-  It is recommended to lay the computer down with the pull tab at the top to allow it to be easily opened.
-  It is also worth mentioning at this point that for complete safety when working inside the computer that wearing an anti-static band and touching a grounded metal object before starting is good practise.


Step 2



-  In order to remove the side panel a single screw needs to first be removed.
-  The side panel can then be pulled towards the back of the computer using the pull tab provided.
-  The panel then needs to be rotated as showed in order to remove it from the computer.

This document was generated on 2020-11-21 09:37:27 PM (MST).


Step 3




- Firstly the power and Sata cables should be disconnected - they can be removed by just pulling them straight back.

 After this is done it should look like the second picture.


- Lastly four screws need to be removed that secure the Hard Drive to the case.


 Extreme care should be take here as the Hard Drive should be supported when loosening off the last screw. Be careful not to press on the casing and only hold it by the edges.

Step 4



- The computer should now look like the first picture.

 While still supporting the Hard Drive by the edges slowly pull it towards you as shown and out of the computer.

 Make sure you keep it in a safe place and don't apply any force to the top cover.

To reassemble your device, follow these instructions in reverse order.